

# 24 Volt ASi Gateways in Stainless Steel

Bihl  
+ Wiedemann

## 24 Volt ASi:

- The devices can be operated directly on a 24 V (PELV) power supply.
- With integrated data coupling coils and adjustable self-resetting fuses optimized for safe use also of powerful 24 V power supplies.

## Available fieldbus interfaces:

- EtherNet/IP + Modbus/TCP in one device

## Recognition of duplicate ASi addresses

## ASi Noise Detector integrated



(figure similar)

Figure	Type	Model	Fieldbus interface <sup>(1)</sup>	Number of ASi networks, number of ASi Master <sup>(2)</sup>	Recognition of duplicate ASi addresses <sup>(3)</sup>	ASi fault detector <sup>(4)</sup>	Programming in C <sup>(5)</sup>	Article no.
	24 Volt ASi Gateway	Gateway	EtherNet/IP + Modbus TCP	1 ASi network, 1 ASi-3 Master	yes	yes	no	<b>BWU3050</b>

<sup>(1)</sup> **Fieldbus interface**

Communication interface between fieldbus and gateway: interfaces for standardized fieldbus systems in industrial automation.

<sup>(2)</sup> **Number of ASi networks, number of ASi Master**

"Single Master": 1 ASi network, 1 ASi-3 Master.

<sup>(3)</sup> **Recognition of duplicate ASi addresses**

Detects whether the same address has been assigned to two ASi nodes. Frequent error when using a handheld addressing device.

<sup>(4)</sup> **ASi fault detector**

Checks the ASi line for interference effects such as noise, external voltages, ...

<sup>(5)</sup> **Programming in C**

Using a C-program offers the possibility to run mini-PLC functions with a gateway.

# 24 Volt ASi Gateways in Stainless Steel



<b>Article no.</b>	BWU3050
<b>Fieldbus Interface</b>	
Type	EtherNet/IP + Modbus TCP (RJ-45) 2 x RJ-45, integrated 2-Port-Switch Ethernet + Modbus TCP acc. to IEEE 802.3
Baud rates	Full duplex (10/100 MBaud, both fieldbus ports must use the same data rate) <sup>(1)</sup>
Variably configurable Assembly Objects	yes
Function	Device Level Ring (DLR) (Ethernet/IP only)
Card slot	chip card for storage of configuration data
<b>ASi</b>	
ASi specification	3.0
Cycle time	150 µs * (number of ASi-3 nodes + 2)
Operating voltage	24 V <sub>DC</sub> (20 ... 31,6 V) (PELV voltage)
Operating current	approx. 250 mA
Current per ASi network	max. 4 A
Length of ASi cable	with 24 V standard power supply: max. 50 m with 30 V ASi power supply: max. 100 m
<b>Display</b>	
LCD	menu, indication of ASi addresses, error messages in plain text
LED power (green)	power ON
LED net (green)	EtherNet communication active
LED config error (red)	configuration error
LED U ASi (green)	ASi voltage o.k.
LED ASi active (green)	ASi normal operation active
LED prg enable (green)	automatic address programming enabled
LED prj mode (yellow)	in configuration mode
<b>UL-specifications (UL508)</b>	
External protection	An isolated source with a secondary open circuit voltage of ≤30 V <sub>DC</sub> with a 3 A maximum over current protection. Over current protection is not required when a Class 2 source is employed.
In general	UL mark does not provide UL certification for any functional safety rating or aspects of the above devices.
<b>Environment</b>	
Applied standards	EN 60529 EN 61000-6-2 EN 61000-6-4
Operating altitude	max. 2000 m
Operating temperature	0 °C ... +55 °C
Storage temperature	-25 °C ... +85 °C
Housing	Stainless Steel, for DIN rail mounting
Pollution Degree	2
Protection category	IP20
Tolerable loading referring to humidity	according to EN 61131-2
Maximum tolerable shock and vibration stress	according to EN 61131-2
Voltage of insulation	≥500 V
Weight	500 g
Dimensions (W / H / D in mm)	85 / 120 / 83

<sup>(1)</sup> from Ident.No. ≥20169 full duplex (10/100 MBaud)

Article no.	BWU3050
Redundant power supply out of ASi: all fundamental functions of the device remain available even in case of power failure in one of the two ASi networks	-
Current measurement of the ASi circuits	-
Self-resetting fuses	•
Adjustable fuses	-
ASi earth fault monitor distinguishes between ASi cable and sensor cable	-
In version 1 gateway, 1 power supply for 2 ASi circuits: only 1 Gateway + 1 ASi power supply for 2 ASi networks	•

## Accessories:

- Diagnostic Software (art. no. BW2902)
- PROFINET Master Simulator (art. no. BW3035, BW3057)
- PROFIBUS Master Simulator (art. no. BW1131, BW1257)
- Power supplies, e.g.: ASi power supply, 4 A (art. no. BW1649), ASi power supply, 8 A (art. no. BW1997)  
(further power supply units can be found at [www.bihl-wiedemann.de/en/products/accessories/power-supplies](http://www.bihl-wiedemann.de/en/products/accessories/power-supplies))
- Control III, Programming in C (art. no. BW2582)